


PATENT
5181-71501
P5144

"EXPRESS MAIL" MAILING LABEL
NUMBER EL726369962

DATE OF DEPOSIT 3/16/01

I HEREBY CERTIFY THAT THIS PAPER OR
FEE IS BEING DEPOSITED WITH THE
UNITED STATES POSTAL SERVICE
"EXPRESS MAIL POST OFFICE TO
ADDRESSEE" SERVICE UNDER 37 C.F.R. §
1.10 ON THE DATE INDICATED ABOVE
AND IS ADDRESSED TO THE ASSISTANT
COMMISSIONER FOR PATENTS, BOX
PATENT APPLICATION, WASHINGTON,
D.C. 20231


Derrick Brown

**A POWER DISTRIBUTION SYSTEM WITH A DEDICATED POWER STRUCTURE
AND A HIGH PERFORMANCE VOLTAGE REGULATOR**

By:

Larry D. Smith, Istvan Novak, and Michael C. Freda

Atty. Dkt. No.: 5181-71500

B. Noel Kivlin/EAH
Conley, Rose & Tayon, P.C.
P.O. Box 398
Austin, TX 78767-0398
Ph: (512) 476-1400

BACKGROUND OF THE INVENTION

Priority Data

This application claims priority to U.S. provisional application serial number
5 60/244,399, entitled "Power Distribution System with a Dedicated Power Structure and a
High Performance Voltage Regulator" filed October 30, 2000.

1. Field of the Invention

10 This invention relates to electronic circuits, and more particularly, to the
distribution of power to electronic circuits.

2. Description of the Relevant Art

15 With each new generation of computer systems, performance demands increase.
One such demand relates to power distribution systems, which are required to supply
increasing currents at lower voltages and lower impedances. These demands make design
of a power distribution system increasingly difficult.

20 In many computer systems, processors and application specific integrated circuits
(ASICs) are the chief consumers of power. Power is typically delivered to these
components through a printed circuit board (PCB). Power distribution to a processor or
ASIC can consume a significant portion of PCB resources, and is but one of several
competing demands which must be considered during the PCB's design. Other demands
25 include signal distribution and routing, component mounting, connector mounting, and so
on. These demands are often times in conflict with one another, and thus compromises
must be made to the design of the PCB. Such compromises may result in a less than
optimal solution in addressing some or all of these demands.

Power distribution on a PCB typically involves at least one pair of copper planes (a power plane and a ground plane), along with a number of decoupling capacitors, typically mounted on a surface of the PCB. Since the PCB must also accommodate signal traces for a number of signals, the copper planes are often times perforated by holes known as vias. The presence of these signal vias may have a tendency to increase the inductance of the copper planes, which in turn results in an increase in impedance. Inductive impedance can be expressed by the formula $Z = 2\pi fL$, wherein Z is the impedance, f is the frequency, and L is the inductance. Thus, the impedance of the power distribution system may be affected in large part by both the number of signal vias, as well as the frequency at which the computer system is designed to operate.

Further compounding problems of power distribution on a PCB is the fact that many computer systems required different voltages for various components. This may increase the number of copper planes needed for power distribution, as each voltage may require a separate power plane, and often times will have a separate ground plane as well. This may further increase the number of vias necessary in the PCB, thereby increasing the inductance of each of the power planes.

SUMMARY OF THE INVENTION

The problems outlined above may be solved in large part by a system and method for distributing power to an integrated circuit. In one embodiment, a power laminate may be mounted to a printed circuit board (PCB). The integrated circuit for which power is to be distributed may be electrically coupled to the PCB. The power laminate may include one or more power planes and one or more reference (i.e. ground) planes, with each pair of power/reference planes separated by a dielectric layer. The power laminate may also include a connector or other means for receiving power from an external power source.

The power laminate may be electrically coupled to the integrated circuit, thereby enabling it to provide core power to the integrated circuit. The power laminate may also include a voltage regulator circuit, and a plurality of decoupling capacitors.

5 The PCB may include a signal layer for conveying signals to and from the integrated circuit, but does not include any means for directly providing core power to the integrated circuit. Thus, all core power provided to the integrated circuit may be supplied by the power laminate. However, the PCB may include one or more pair of copper planes (e.g. a pair including a power plane and a reference plane) for providing power to
10 other components mounted upon the PCB.

As used herein, the term "core power" refers to that power having a specific voltage and a specific current that is supplied to the integrated circuit itself. For example, one embodiment of an integrated circuit may require a core power having a voltage of 1.2
15 volts and a maximum current of 20 amperes. The PCB may be configured for providing power to other components mounted upon it. In one embodiment, the integrated circuit may require power at a low voltage, such as 1.2 volts, for high-frequency operation, while other components mounted upon the PCB which operate at a lower frequency may be configured to receive power with a higher voltage, such as 5 volts. One embodiment of
20 the power laminate having a voltage regulator may be configured to receive power from the PCB to which it is mounted, whereupon the voltage regulator may convert this power into the core power required by the integrated circuit. In another embodiment, the power laminate (and thus the voltage regulator, if present) may be configured to receive power from a source external to the PCB.

25

In one embodiment, a power laminate may be mounted on the bottom of a PCB, with the integrated circuit mounted on top. The power laminate and the integrated circuit may be attached to the PCB by soldering, and one or both may include an array of solder

balls known as a ball-grid array. Alternatively, the power laminate may include a land-grid array, in lieu of a BGA, for mounting it to the PCB.

5 In another embodiment, the power laminate may be arranged between the integrated circuit and the PCB. The power laminate may have at least one aperture to allow the passage of signals between the PCB and the integrated circuit.

10 The power laminate may include a voltage regulator circuit. The voltage regulator circuit may be implemented with either discrete components or with a voltage regulator module. In one embodiment, the voltage regulator may be a switching voltage regulator. The switching voltage regulator may include an inductor for translating energy from one voltage to another, and a capacitor to supply current in times of heavy or transient demands by the integrated circuit. A switch coupling the inductor to a reference plane may enable some of the energy to be drained from the inductor when the ability of
15 the voltage regulator to supply current exceeds the current demand of the integrated circuit.

20 The power laminate may also include a plurality of decoupling capacitors. In one embodiment, the decoupling capacitors may be surface-mounted capacitors. Mounting the decoupling capacitors on the power laminate may save a significant amount of space on the PCB.

25 Thus, in various embodiments, the system for distributing power to an integrated circuit including a power laminate may provide various advantages. By distributing power to the integrated circuit using a power laminate, a PCB may be optimized for signal distribution and routing, while the power laminate is optimized for core power distribution. Compromises to both core power distribution and signal distribution that occur when both are implemented on the PCB may be avoided. Placing all core power distribution functions on the power laminate, including a voltage regulator circuit and

decoupling capacitors may result in a significant savings of space on the PCB.

Furthermore, distribution of core power by a power laminate may result in a power connection with lower inductance than can be achieved by distributing power on the PCB. This low-inductance power connection may result in a significant lowering of impedance in the power distribution system. With a low impedance power connection, power may flow more easily from the power distribution system to the integrated circuit.

BRIEF DESCRIPTION OF THE DRAWINGS

Other objects and advantages of the invention will become apparent upon reading the following detailed description and upon reference to the accompanying drawings in which:

Figure 1 is a drawing illustrating one embodiment of a power distribution system for an integrated circuit, the power distribution system including a power laminate with decoupling capacitors;

Figure 2 is an drawing illustrating one embodiment of a power distribution system for an integrated circuit including two voltage regulator modules;

Figure 3 is drawing illustrating one embodiment of a power distribution system for an integrated circuit, the power distribution system including a power laminate with decoupling capacitors and a bolster plate;

Figure 4 is a drawing illustrating a cutaway view of a power distribution system including one embodiment of a power laminate, wherein the power laminate is arranged between an integrated circuit and a printed circuit board;

Figure 5 is a drawing illustrating a cutaway view of a power distribution system including another embodiment of a power laminate, wherein the power laminate is arranged between an integrated circuit and a printed circuit board;

Figure 6 is a drawing illustrating a cutaway view of a power distribution system including an embodiment of a power laminate mounted to a printed circuit board, with an integrated circuit mounted upon the opposite side of the printed circuit board; and

Figure 7 is a schematic diagram of one embodiment of a voltage regulator circuit that may be included in the power distribution system.

While the invention is susceptible to various modifications and alternative forms,
5 specific embodiments thereof are shown by way of example in the drawings and will
herein be described in detail. It should be understood, however, that the drawings and
description thereto are not intended to limit the invention to the particular form disclosed,
but, on the contrary, the invention is to cover all modifications, equivalents, and
alternatives falling within the spirit and scope of the present invention as defined by the
10 appended claims.

DETAILED DESCRIPTION OF THE INVENTION

15 Turning now to Figure 1, a drawing illustrating one embodiment of a power
distribution system, including a power laminate, for an integrated circuit is shown.
Integrated circuit 5 is mounted to printed circuit board (PCB) 15 by solder balls 25,
which are part of a ball-grid array (BGA). Heat sink 30 may be mounted upon integrated
circuit 5 for the purposes of dissipating heat.

20 Power laminate 20 may be mounted to PCB 15 on the opposite side of integrated
circuit 5, also by a BGA. Power laminate 20 may be configured for the distribution of all
power to integrated circuit 5. Power laminate 20 may include at least one power plane
and one reference (e.g. ground) plane. In the embodiment shown, PCB 15 does not
25 include power or ground planes for providing power to the integrated circuit, and thus is
not configured for providing power to the integrated circuit. This may allow PCB 15 to
be optimized for signal distribution, while power laminate 20 is optimized for power
distribution. PCB 15 may include one or more signal layers, each with a plurality of
signal traces, for conveying signals to and from integrated circuit 5.

As used herein, the term “core power” may refer to power having a specific voltage and specific current to be provided to integrated circuit 5, and which may be different from power provided to other components mounted upon PCB 15. For example, integrated circuit 5 may require a core power of 1.2 volts at a maximum of 20 amperes of current, while other components mounted on PCB 15 may require 5-volt power.

A connector or other connecting means for connecting an external power source to power laminate 20 may be present in various embodiments. In various embodiments, the connecting means may be virtually any type of connector that may be mounted to power laminate 20. In another embodiment, power laminate 20 may include pads for soldering wires from an external power source to both the power and reference planes of power laminate 20. The particular means for connecting an external power source to power laminate 20 may be chosen to best suit the particular implementation of the power distribution system. Power may also be delivered to power laminate 20 through PCB 15.

In one embodiment, PCB 15 may deliver power at a first voltage, such as 5 volts, to power laminate 20. Power laminate 20 may include a voltage regulator circuit which may then convert the 5-volt power received to the core power required by integrated circuit 5 (e.g. 1.2 volts at 20 amperes). Voltage regulator circuitry for power laminate 20 will be discussed in further detail below.

In the embodiment shown, power laminate 20 includes a plurality of decoupling capacitors 40. In the embodiment shown, decoupling capacitors 40 may be surface mounted capacitors, and may be used to provide additional decoupling capacitance for the power distribution system. In some embodiments, decoupling capacitors may not be required, as power laminate 20 itself may be a significant source of decoupling capacitance. However, if extra decoupling capacitance is necessary, power laminate 20 may be easily configured to allow for the mounting of capacitors.

Moving now to Figure 2, a drawing illustrating an embodiment of a power distribution system, including power laminate 20 with voltage regulator circuit 1000 and bolster plate 21 is shown. In the embodiment shown, both integrated circuit 5 and power laminate 20 are each mounted to PCB 15 by land-grid arrays (LGA) 26. The use of LGA 26 instead of a BGA or other type of solder connection may be useful in embodiments in which a large amount of heat is generated by integrated circuit 5.

In the embodiment shown, bolster plate 21 is mounted directly beneath power laminate 20. Bolster plate 21 may include insulator 22 for electrical and/or electromagnetic isolation from power laminate 20. Fasteners 27 may be used to secure bolster plate 21 to power laminate 20, as well as securing heat sink 30 to integrated circuit 5. Bolster plate 21 may provide protection to the assembly shown during handling (e.g. installing the assembly in a computer system chassis). Bolster plate 21 may provide structural stability to power laminate 20, which, in some embodiments, may be a flexible structure.

In the embodiment shown, voltage regulator circuit 1000 may be implemented in a single package (i.e. a voltage regulator module). Alternate embodiments, wherein a voltage regulator circuit is implemented using discrete components, are possible and contemplated. In some embodiments, power laminate 20 may be a flexible structure, and may therefore include a stiffener for voltage regulator circuit 1000. Voltage regulator circuit 1000 may be configured to receive a first voltage from an external power source and convert it to a second voltage, which may then be supplied to a load such as integrated circuit 5. Additional details for voltage regulator circuit 1000 will be discussed below.

Figure 3 is a drawing illustrating of one embodiment of a power distribution system for integrated circuit 5, the power distribution system including power laminate 20, decoupling capacitors 40, and bolster plate 21. The embodiment shown may be

similar to that illustrated in Figure 2, with the exception that power laminate 20 is mounted on the opposite side of PCB 15 from integrated circuit 5. Although not explicitly shown here, power laminate 20 may also include a voltage regulator circuit, such as voltage regulator 1000 shown in Figure 2.

5

Figure 4 is a drawing illustrating a cutaway view of a power distribution system including one embodiment of power laminate 20, wherein power laminate 20 is arranged between integrated circuit 5 and a PCB 15. In the embodiment shown, power laminate 20 is shown in a cutaway view, and is arranged between integrated circuit 5 and PCB 15.

10 Power laminate 20 includes a power plane 201 and a reference plane 202, separated by dielectric layer 203. Dielectric layer 203 may be made of any dielectric material, and its thickness may vary according to the needs for the particular implementation. Power plane 201 and reference plane 202 may be constructed of a conductive material, such as copper or other metals with electrically conductive properties.

15

In the embodiment shown, both power plane 201 and reference plane 202 include a plurality of apertures to allow signals to pass from integrated circuit 5 to PCB 15. Power plane 201 may include additional apertures to allow for the connection of reference plane 202 to integrated circuit 5. Signal connections 215 may be arranged to
20 allow the passage of signals between integrated circuit 5 and PCB 15. Power connections 211 may connect directly from power plane 201 to integrated circuit 5, thereby providing it with power. Ground connections 212 may connect reference plane 202 to integrated circuit 5, thereby providing a current return path.

25

Capacitors 40 may also be included in various embodiments of power laminate 20. In the embodiment shown, capacitors 40 are surface-mounted capacitors mounted to one side of power laminate 20. Various types of capacitor packages may be used, and capacitors 40 may be mounted upon either side of the power laminate. Capacitors 40 may be used to provide additional decoupling capacitance (over that provided by the

power laminate itself) within the power distribution system. In addition, the embodiment shown here for power laminate 20 may be configured to accommodate a voltage regulator circuit.

5 Figure 5 is a drawing illustrating a cutaway view of a power distribution system including another embodiment of a power laminate, wherein power laminate 20 is arranged between integrated circuit 5 and PCB 15. In the embodiment shown, power laminate 20 includes a large, centrally located aperture in order to allow signals to pass between integrated circuit 5 and PCB 15. The signals may be conveyed between
10 integrated circuit 5 and PCB 15 by signal connections 215, which pass through the aperture in power laminate 20. Power plane 201 may be electrically connected to integrated circuit 5 by power connections 211, thereby providing it with power.

 In the embodiment shown, the width of reference plane 202 is slightly larger than
15 the width of power plane 201. In this embodiment, reference plane 202 may be connected to integrated circuit 5 by ground connections 212. Ground connections 212 may be arranged along the periphery of reference plane 202. This may allow reference plane 202 to be coupled to integrated circuit 5 without the need for additional apertures in power plane 201 (although apertures in dielectric layer 203 may be present). Apertures in
20 the planes may give rise to inductance within the planes, which in turn may increase the impedance of the power distribution system. By extending the dimensions of reference plane 202 to allow it to be connected to integrated circuit 5 without the need for more apertures in power plane 201, additional inductance may be avoided. Other
embodiments, wherein the arrangement of power plane 201 and reference plane 202 are
25 reversed (i.e. power plane 201 having extended dimension with power connectors 211 arranged on the periphery) are possible and contemplated.

 Figure 6 is a drawing illustrating a cutaway view of a power distribution system including an embodiment of power laminate 20 mounted to a PCB 15, with integrated

circuit 5 mounted upon the opposite side of PCB 15. In the embodiment shown, both power laminate 20 and integrated circuit 5 are mounted to PCB 15 by solder balls 25. Solder balls 25 connecting power laminate 20 to PCB 15 may be part of a ball-grid array. Similarly, solder balls 25 connecting integrated circuit 5 to PCB 15 may also be part of a ball-grid array.

Both power plane 201 and reference plane 202 may be connected to integrated circuit 5 by conductors 207, which pass through PCB 15. In one embodiment, conductors 207 are terminated at solder pads configured for accommodating solder balls on both the top and bottom of PCB 15.

In the embodiment shown, power plane 201 may be free of apertures, which may be required in other embodiments to allow for connections for signals and connections to the reference plane. In this embodiment, connections for power plane 201 may be centrally located on power laminate 20 and integrated circuit 5. Reference plane 202 may have a larger width (or length) than power plane 202, and thus, connections to PCB 15 may be arranged closer to the peripheral of power laminate 20 than those connections for power plane 201. This may help in eliminating the need for apertures in power plane 201. The elimination of apertures in power plane 201 and/or reference plane 202 may result in lower inductance (and thus, lower impedance) in the power distribution system.

It should be noted that embodiments wherein the arrangement of power plane 201 and reference plane 202 is the opposite as shown (i.e. reference plane 202 on top and nearer to PCB 15 than power plane 201) are possible and contemplated.

PCB 15 may include a plurality of signal traces 36 for conveying signals to and from integrated circuit 5. These signals may be conveyed from PCB 15 to integrated circuit 5 through LGA 26. Signal connections on integrated circuit 5 may be arranged towards the peripheries of the integrated circuit package. This arrangement of signal

connections from integrated circuit 5 to the signal traces 36 of PCB 15 may allow for unobstructed electrical paths (i.e. conductors 207) from both power plane 201 and reference plane 202 to integrated circuit 5. This may in turn allow for greater optimization of PCB 15 for conveying signals, as well as greater optimization of power laminate 20 for power distribution.

The various arrangements of the power laminate (with respect to the PCB and the integrated circuit) shown above each provide certain advantages and disadvantages. Embodiments where the power laminate is arranged between the PCB and integrated circuit may result in a significant savings of circuit board area, as the area on the PCB opposite the integrated is not used for mounting the power laminate. However, such embodiments may require apertures to allow for signals to pass between the integrated circuit and the PCB. This may result in a greater inductance associated with power laminate (as opposed to embodiments wherein there are no apertures in the power and/or reference planes), and thus the impedance of the power distribution system. However, the inductance (and thus impedance) of such an embodiment may be significantly lower than if the power and reference planes are located within the PCB itself.

Moving now to Figure 7, a schematic diagram of one embodiment of a voltage regulator module is shown. Many power distribution systems include voltage regulators, and thus their overall performance and affect on the power distribution system must be factored in to allow optimum selection of decoupling components. A typical voltage regulator may be configured to receive an input voltage from a power source, and provide a second voltage as an output. For example, a voltage regulator circuit might be configured to receive an input voltage of 5 volts, and have an output voltage of 1.8 volts. The voltage regulator may receive the input voltage through a connector. In one embodiment, the connector may comprise one or more solder connections to the PCB, wherein the first voltage is received from the PCB. In another embodiment, the connector may comprise a connector for receiving the input voltage from a source

external to the PCB. The voltage regulator may be designed to ensure a smooth and steady voltage is supplied to a load coupled to it. The load may be any type of circuitry previously discussed in this disclosure, as well as other types of circuitry not explicitly discussed herein.

5

Figure 7 is a schematic diagram of one embodiment of a voltage regulator which could be used in a power distribution system, such as those discussed above. Voltage regulator circuit 1000, in this embodiment, is a switching voltage regulator. Voltage regulator 1000 includes voltage source V , which is the input voltage to the circuit.

10 Inductor L_1 in the circuit has the function of storing energy when switch S_1 is closed (and switch S_2 is open). By storing energy, inductor L_1 may allow current to be delivered to the load. If the current supplied through inductor L_1 is more than the current demanded by the load, switch S_1 may open, while switch S_2 may close. This may allow the excess current to drain through switch S_2 . When a sufficient amount of current has been drained,
15 switch S_2 may open and S_1 may close. Inductor L_1 may then resume storing energy.

The control of switches S_1 and S_2 may be performed by amplifier A. Amplifier A may be configured to sense a load voltage with respect to a reference voltage (shown here as V_{ref}). If amplifier A senses that load voltage is too high, it may close S_2 and open S_1 ,
20 thereby causing inductor L_1 to ramp down the current, as described above. If amplifier A senses that load voltage is too low, it may close S_1 and open S_2 , thereby causing inductor L_1 to ramp up current. Current from inductor L_1 may be integrated by capacitor C_1 , which may smooth out the voltage across the load. Resistor R_{ESR} is not an actual resistor in the circuit, but rather is shown to represent the equivalent series resistance provided by
25 capacitor C_1 .

The circuit also includes inductor L_{out} , which represents the output inductance seen by the voltage regulator circuit. This inductance may be present in circuit traces of a printed circuit board, wires, pins of a package in which the voltage regulator or the load is

contained within, or other type of transmission line. Also shown in the schematic is resistor R_o , which represents the resistance provided by the load. As with resistor R_{ESR} , neither of these circuit elements are actual components, but are shown to represent quantities that must be taken into account when designing the power distribution system.

5

An essential parameter for the voltage regulator circuit shown is the amount of time taken to respond to a current transient. For example, suppose the load is a microprocessor which may demand a current of 20 amperes for some period of time. Further, suppose the input voltage to the circuit is 5 volts, the output voltage (i.e. the regulated voltage, or core power voltage supplied to the integrated circuit) is 1.8 volts,
10 and the inductance of L1 is 0.82 μ H. Recall that the voltage across an inductor may be expressed by the equation $V = L \cdot (di/dt)$, wherein V is the voltage, L is the inductance, and di/dt is the rate of change of current with respect to time. Rearranging the equation to solve for time, we have $dt = di(L/V)$. Inserting the values shown above (20 amps, 0.82
15 μ H, and with $V = 5 \text{ v} - 1.8 \text{ v} = 3.2 \text{ v}$) into the equation, the response time is 5.13 microseconds. This response time represents a theoretical best-case scenario, whereas in practice, a good estimate may be twice the theoretical best. The response shown here represents rise time of the current. Similarly, the fall time of the current, which may occur when the microprocessor suddenly stops drawing current, may be calculated using
20 the same equation, except in this case the voltage used in the calculation is the output voltage of the voltage regulator circuit (1.8 v). Substituting these values into the equation, a current fall time of 9.11 microseconds is found to be the theoretical best current fall time.

25 In various embodiments, two main types of inductance may be associated with the power laminate (or power distribution systems in general). Horizontal inductance may be primarily associated with a plane, such as a copper plane used as a power or reference plane. Vertical inductance may primarily be associated with connections to the integrated

circuit, or connections from the power laminate to the PCB (e.g. solder balls). Horizontal inductance may be 3-4 times greater than the vertical inductance, and possibly greater when apertures such as signal vias are factored in. By moving power distribution off of a PCB and onto a power laminate, a significant amount of this inductance may be eliminated, resulting in a power distribution system with lower impedance.

Horizontal inductance may be minimized in various ways. Eliminating or minimizing the number of apertures in a power plane (or reference plane) may keep the horizontal inductance at a minimum. In some embodiments where signals must pass through the power laminate, inductance may be minimized by the use of multiple power and/or reference planes. In one embodiment, both the power and reference plane may be divided into multiple pairs of planes, with each pair in an electrically parallel configuration with respect to the other pairs. This may be an effective way to minimize the inductance associated with these types of embodiments. For example, an embodiment with 3 pairs of power/reference planes placed in parallel with each other may have an inductance that is 1/3 of the value of an embodiment using a single power/reference plane pair. Using a very thin dielectric between a power plane and an associated ground plane may also be an effective method of reducing horizontal inductance.

Vertical inductance may be minimized by using more vertical structures in order to mount the power laminate. An example of a vertical structure would be the solder balls of a BGA, as shown in various embodiments above, or the connections associated with an LGA. Since the power laminate is separate from the PCB, and thus must be mounted to it, a large number of vertical structures may be used, thereby minimizing vertical inductance.

By reducing both horizontal and vertical inductance, the overall impedance of a power distribution system for an integrated circuit may be greatly reduced. In one

embodiment, a power distribution system including a power laminate may be as low as 10 Pico-henries (pH).

While the present invention has been described with reference to particular
5 embodiments, it will be understood that the embodiments are illustrative and that the invention scope is not so limited. Any variations, modifications, additions, and improvements to the embodiments described are possible. These variations, modifications, additions, and improvements may fall within the scope of the inventions as detailed within the following claims.

10

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
221